

Doors™ v4.58

Release Notes

1.0 Doors v4.58

Doors v4.58 makes two program corrections.

1. On some EntraGuard Platinum units, performing a “Smart Update” on Doors would cause the keypad to lock up. The EntraGuard Platinum unit would display “Updating, please stand by” and remain in this state until either the power was cycled to the unit or a “Total Update” was performed from Doors. The cause of this type of situation has been fixed.
2. On some EntraGuard Titanium and Silver units, performing a “Smart Update,” “Total Update,” or “Operate Doors > Update Doors” on Doors would cause any future keypad commands to be ignored by the EntraGuard unit. The EntraGuard Titanium or Silver unit would remain in this state until power was cycled to the unit. This issue has been fixed.

NOTE: *Upgrading the Doors software to v4.58 requires the following associated upgrades only when an EntraGuard unit is in use in the network:*

- **PXL-500/PXL-510 v8.4.51**
- **EntraGuard Platinum v9.1.4**
- **EntraGuard Titanium/Silver v7.4.03**

2.0 Compatibility

Doors software only supports PXL-250, PXL-500, PXL-510, EntraGuard Titanium, EntraGuard Silver, and EntraGuard Platinum controllers. For proper operation of *Doors* v4.58 software, the following controller requirements must be met.

NOTE: *For all controllers, you can use downlevel firmware revisions, but if the controller firmware does not meet minimum revision levels listed below, new program features will not be available for use as these features are not implemented in the downlevel firmware releases.*

For PXL-500 Only Networks

- For complete software/firmware compatibility, *Doors* v4.58 software **MUST** be used with PXL-500 controllers using firmware revision 8.4.51 or higher.
- For complete software/firmware compatibility, *Doors* v4.58 software **MUST** be used with PXL-510 controllers using firmware revision 8.4.51 or higher, and PIC v2.11 or higher.
- In Alarm Control applications, a PXL-510 **MUST** be the master controller.

For EntraGuard Only Networks

- For complete software/firmware compatibility, *Doors* v4.58 software **MUST** be used with EntraGuard Titanium and EntraGuard Silver controllers using firmware revision 7.4.03 or higher, and PIC release 1.03 or higher.
- For complete software/firmware compatibility, *Doors* v4.58 software **MUST** be used with EntraGuard Platinum controllers using firmware revision 9.1.4 or higher, and PIC16 v1.0.10 and PIC18 v1.0.1 or higher.

For PXL-250 Only Networks

- For complete software/firmware compatibility, *Doors* v4.58 software **MUST** be used with PXL-250 controllers using firmware revision 6.3.20 or higher.

Doors™ v4.58

Release Notes

For Mixed Controller Type Networks (mixing PXL-500s, PXL-250s, and/or EntraGuard)

- To use the Alarm Control feature, a PXL-510 must be the master controller on the network.
- To use the Temp Cards feature, a PXL-500 or PXL-510 controller must be the master controller on the network.
- A PXL-500 or PXL-510 may be used as a slave controller on a network with a PXL-250 master controller, however features that require a PXL-500 or PXL-510 to be the master controller (e.g. Temp Users and Alarm Control) will not be available.
- A PXL-500 or PXL-510 may be used as a slave controller with an EntraGuard Titanium, EntraGuard Silver, or EntraGuard Platinum as the master controller.
- In a mixed network of PXL-250s and EntraGuard Titanium, EntraGuard Silver, or EntraGuard Platinum controllers, an EntraGuard controller must be the master controller in the network. There is no such requirement in a mixed network of PXL-500s or PXL-510s and EntraGuards.

For Badging

- GuardDraw software v5.3 contained within this release is compatible with *Doors* v3.74 or later releases only.

NOTE: For specific compatibility information, refer to the [Series 3 and 4 Compatibility Guide](#) (P/N 01876-001).

3.0 The Keri CD-ROM Autorun Program

The Keri CD-ROM has an autorun program that opens a menu which allows you to easily locate all installation programs, and technical and marketing documentation stored on the Keri CD. Insert the CD into your computer.

- If your host computer's autorun feature is enabled, the autorun menu appears.
- If the autorun feature is not enabled, use Windows™ Explorer to browse the Keri CD. Locate and start the “autorun.exe” program to open the autorun menu.

4.0 Product Documentation

The Keri CD-ROM includes copies of technical and marketing documentation in Adobe Acrobat® PDF format. The autorun menu includes links to the major documentation sections of the Keri CD. All documentation is stored in Adobe's PDF format, and can be viewed using the Adobe Acrobat Reader program. The Adobe PDF format is a universal document display format that allows you to view and print copies of documents. The autorun menu includes a link to the free Adobe Acrobat Reader installation program on Adobe's web site.

NOTE: The documents on the Keri CD are the current revisions at the time of CD release. However, these documents are subject to change at any time. If necessary, please contact Tech Support at Keri Systems or view the Technical Documentation Downloads section of the Keri web page to verify the current revision of any document (www.kerisys.com/pages/download/techdocs.asp).

Contact Keri Systems:

Keri USA	Keri UK, Ireland, Europe
2305 Bering Drive San Jose, CA 95131	Unit 17 Park Farm Industrial Estate Ermine Street Buntingford Herts SG9 9AZ UK
Telephone: (800) 260-5265 (408) 435-8400	Telephone: + 44 (0) 870 444 7234
Fax: (408) 435-7163	Fax: + 44 (0) 1763 274 106
Web: www.kerisys.com	Web: www.kerisystems.co.uk
E-mail: sales@kerisys.com techsupport@kerisys.com	E-mail: sales@kerisystems.co.uk tech-support@kerisystems.co.uk

End of document.